

## Device Inspection Guide

### Overview and Form Factor

#### Overview

DynaFlex II PED Kiosk Products are secure card reader authenticators that deliver magstripe, EMV Contact Chip, EMV Contactless, and NFC contactless reading capability with a flat mounting backing. DynaFlex II Kiosk BCR additionally offers barcode reading and DynaFlex II Kiosk PED offers a touchscreen for signature capture, manual entry of card data, and PIN entry for POS and banking applications.

#### Top

The top of the device is smooth, with no extraneous wires or elements. BCR models are raised to accommodate the camera.

#### Front Face

##### BCR Devices Only - Barcode Reader

BCR (barcode reading) devices have a camera lens that is surrounded by a barcode icon. In barcode reader models, a barcode reader is along the top of the reader.

##### Chip Card Insertion Slot

The card slot for the EMV Contact Chip reader is a smooth, unobstructed path. Other than the contact points that read the chip there are no electronics, mechanics, or wires in the path.

##### LEDs

There are four LED lights between the chip card insertion slot and the magnetic stripe swipe path. These provide signals to the user. See installation and operation manual for complete LED signaling.

##### Swipe Path

The swipe path is smooth. The only moving part is the spring-mounted read head that depresses into the device as the card's magnetic stripe makes contact with the read head. There are no mechanics, electronics, or wires in the path.

##### Contactless Landing Zone

There is an all-in-one screen: touchscreen, contactless landing zone, and LCD display. The display is back-lit. Look for any signs of tampering or a false screen overlay. The screen is inset and measures 2.27in. (57.60mm) X 1.70 in. (43.20mm). The contactless landing zone is hidden behind the screen. User's fingertips capture signatures instead of a stylus.

#### Sides

The right and left side are smooth with a clear demarcation for the fixed kiosk mount.

#### Form Factor

Check the overall form factor for signs of attempted entry. Directional icons may be printed on your device. DynaFlex products are made from molded rubberized black plastic with matching black lens on the face. There are no additional electronics or wires. Any breaks in the plastic, scuffs, or damage could be signs of physical tampering and should be reported. Look for any added components, size, or weight.

	DynaFlex II PED Kiosk	DynaFlex II PED Kiosk BCR
Dimensions	4.1 x 3.5 x 1.9 in. (103.3 x 90.0 x 48.3 mm)	4.1 x 3.7 x 1.9 in. (103.3 x 95.1 x 48.3 mm)
Weight	USB: 9.6 oz. (276 g) WLAN: 8.9 oz. (252 g)	USB: 9.92 oz (279.5 g) WLAN: 10.12 oz (285.5 oz)



#### Bottom

Carefully inspect the form factor. Ensure there are no additional electronics, wires or forms added to the device.

##### Certificate Logos

Certification logos and patent information are imprinted in the plastic form factor.

##### USB-C Cable

The device uses a USB-C cable with ferrite sleeve at each end to power and/or charge. Ensure there are no extraneous cables and that the cable is connected directly to the host.

##### Pushbutton

Tactile switch/button.

##### Product Label

The product label is located on the underside of the device. The Serial Number, Rev, Date, Part number (PN), MAC ID (MAC) and Hardware PN (HW) are listed as appropriate. Ensure the serial number listed on the back of the device matches the serial number on the display of the device during boot-up for Pro devices; compare the hardware ID to the PCI website confirm validity.

##### FCC/IC Label

The FCC/IC label lists the product model name, FCC ID and IC numbers.

##### Charging

There are four (4) charging contacts on the underside of the device.

##### 4 Threaded Mounting Holes

There are 4 threaded mounting holes.

## Quick Inspection

As part of your inspection, include the following for your device inspection audit:

- Be certain to have a list of the devices and include the details listed on the product label.
- It may be helpful to take photos of the front, back, and side of each device.

Be certain to check device part numbers, serial numbers and IDs and check physical connections. Use the chart below as a checklist to inspect the device for signs of tampering.

Are there signs of tampering:	Signs of tampering	
Site Inspection	YES	NO
Form Factor - check overall form factor		
Front		
Signature Capture (optional - no stylus included)		
Magnetic Stripe Swipe Path		
LCD Display and Contactless Landing Zone		
EMV Chip Card		
Barcode reader		
Sides		
Magnetic Stripe Swipe Path		
Rubberized Shell		
Form Factor		
Cables and charging cradle		
USB-C cable		
Underside and Back		
Certificate Logos (imprinted)		
Form Factor		
Cable Connection		
Pushbutton		
Charging contacts		
Mount		
Labels		
Tripped device		
If there is forced entry, the security switches built into the electronics will be tripped. If they are tripped the sensitive data such as encryption keys and certificates are cleared as part of security measures mandated by PCI and the device will not be available to make transactions.		

### NOTICE:

If the security switches have been tripped, DynaFlex II Kiosk cannot be repaired in the field and must go back to the factory for repair. Follow RMA procedures. Users must report all signs of tampering as per standard protocol.



## Certifications and Validation

### PCI DEVICE VALIDATION

To check for PCI Validation check the Hardware and Firmware ID. Hardware ID is printed on the label. The firmware ID is accessible via a host command and is displayed. Go to the PCI compliance web page and search for MagTek, and find the product name, DynaFlex II PED Kiosk. Compare the

Hardware ID and Firmware ID:

[https://www.pcisecuritystandards.org/assessors\\_and\\_solutions/pin\\_transaction\\_devices](https://www.pcisecuritystandards.org/assessors_and_solutions/pin_transaction_devices)

### EU STATEMENT

Hereby, MagTek Inc. declares that the radio equipment types Wideband Transmission System (Wireless LAN and Bluetooth Low Energy), and Non-Specific Short Range Device (contactless) are in compliance with Directive 2014/53/EU. The full text of the EU declarations of conformity is available at the following internet addresses:

Security Policy <https://www.magtek.com/content/documentationfiles/d998200520.pdf>

### UKCA STATEMENT

Hereby, MagTek Inc. declares that the radio equipment types Wideband Transmission System (Wireless LAN and Bluetooth Low Energy), and Non-Specific Short Range Device (contactless) are in compliance with Radio Equipment Regulations 2017 Directive S.I.2017.1206. The full text of the UKCA declarations of conformity is available at the following internet addresses Security Policy <https://www.magtek.com/content/documentationfiles/d998200520.pdf>

### FEATURES

Some features and functions may be documented, but not available with the current release of the product. Please contact your MagTek representative for questions about specific features and functions and when they are scheduled to become available.

### TRADEMARKS

EMV® is a registered trademark in the U.S. and other countries and an unregistered trademark elsewhere. The EMV trademark is owned by EMVCo, LLC. The Contactless Indicator mark, consisting of four graduating arcs, is a trademark owned by and used with permission of EMVCo, LLC.

